

# e-GeForce 6600 LE

Part Number: **128-P2-N352**

- 128MB
- DDR
- TV-Out
- PCI-E

### At A Glance

- 256-bit GeForce 6600 LE (300MHz clock)
- 128MB 64-bit 5ns (16x16) DDR Memory (200MHz clock - 400MHz effective)
- PCI Express x16 Compatibility (PCI Express Compliant)
- PC 99 DB-15 analog connector (VESA DDC2B + DPMS)
- Integrated NVIDIA TV Encoder (S-Video)
- DVI-I Connector for Analog/Digital Display
- 6.4 GB per second memory bandwidth

### Features

- Superscaler 8-pipe architecture
- CineFX 3.0 Engine
- UltraShadowII Technology
- 64-bit texture filtering and blending
- Intellisample 3.0 Technology
- 128-bit Studio precision computation
- Full speed 32-bit color precision



### Interface

- TV-Out
- DVI-I
- VGA

### Driver Support

- ResChanger<sup>®</sup>
- NVIDIA Unified Driver Architecture (UDA) (Windows 2000/XP/XPx64/MCE 2005)
- Full DirectX 9.0 support
- Full OpenGL ICD for All Supported Operating Systems

### Dimensions

- height: 3.88in - 88.4mm
- length: 7.0in - 177.8mm

### Resolution Chart

|             | 8-Bit | 16-Bit | 32-Bit |
|-------------|-------|--------|--------|
| 640 x 480   | 240Hz | 240Hz  | 240Hz  |
| 800 x 600   | 240Hz | 240Hz  | 240Hz  |
| 1024 x 768  | 240Hz | 240Hz  | 200Hz  |
| 1152 x 864  | 200Hz | 200Hz  | 170Hz  |
| 1280 x 960  | 170Hz | 170Hz  | 150Hz  |
| 1280 x 1024 | 170Hz | 170Hz  | 150Hz  |
| 1600 x 1024 | 120Hz | 120Hz  | 100Hz  |
| 1600 x 1200 | 120Hz | 120Hz  | 100Hz  |
| 1920 x 1080 | 100Hz | 100Hz  | 85Hz   |
| 1920 x 1200 | 100Hz | 100Hz  | 85Hz   |
| 1920 x 1440 | 85Hz  | 85Hz   | 75Hz   |
| 2048 x 1536 | 75Hz  | 75Hz   | 60Hz   |

Refresh rates shown are the highest obtainable and are monitor dependent. Resolutions, pixel depths and refresh rates are driver dependent and may not be available in all applications or operating system.



Gaming  
Imaging  
3D  
Video  
Entertainment  
Photos  
Graphics